

SR Occupancy Sensor

78002 Data Sheet

The 78002 Small-Room Occupancy Sensor provides a unidirectional monitoring pattern, detecting movement over 500 ft², even through glass. Upon detecting movement, the occupancy sensor will activate, sending a signal to the connected TEK3 TekMonitor that the room is occupied. When movement is no longer detected, a countdown timer begins, shutting down the room's A/V equipment once the countdown ends if no further movement is detected.

TEKVOX multi-technology occupancy sensors use both infrared and ultrasonic technology for unparalleled monitoring without creating false triggers. Sensors automatically adjust to a room's usage, allowing for easy install with no programming required. Occupancy sensors allow a room's A/V control system to extend projector lamp life by shutting down equipment in unoccupied rooms. Other benefits include substantial energy savings, control of a room's lights, interfacing with the HVAC system, and room occupancy monitoring for crisis management.

Features:

- 180° motion sensing for up to 500 sq. ft.
- Easy installation w/ single mounting post & 3 color-coded wires for interface to TekMonitor
- Internal processor continually adjusts sensitivity and time delay for optimal performance
- Automatic equipment and lighting shut-down
- Shipped fully functional, pre-programmed, and rigorously tested



SR Occupancy Sensor

78002 Technical Specifications

Multi-Technology	Uses both IR and Ultrasonic sensors
Coverage	180° 500 Sq. Ft.
Output	24 VDC Active High
Transducer Pairs	1
Frequency	40 kHz
Housing	Rugged, high-impact, injection molded plastic
Color	White
Power Requirements	24 VDC, 30 mA
Temperature	32 ~ 104°F (0 ~ 40°C)
Humidity	0 ~ 95%
Product Dimensions	4.5" (114mm) diameter, 1.5" (38mm) height
Product Weight	5 oz. (142g)

Specifications are subject to change without notice